



The **EU7000is** Super Quiet Generator From Honda

7000 watts of portable, fuel injected inverter power means super quiet operation, stable power, longer run time, and lower maintenance. **New CO-MINDER™ advanced carbon monoxide detection system** continuously measures CO levels and automatically shuts down the generator before detected CO levels near the generator become dangerously high.*

FEATURES

- **7000 watts** (58.3A/29.1A) 120/240V Inverter Power
- **Super quiet**, only 52 to 58 dB(A)
- **Fuel injection**, no carburetor related issues
- **Push button electric start** makes starting quick and easy
- **Smartphone enhanced** with  **Bluetooth®** wireless start-stop, operation monitoring, fuel level, and service reminders
- **Fuel efficient**, runs up to 16 hrs. on 5.1 gals. of fuel
- **CO-MINDER™** automatically shuts down the generator if it detects carbon monoxide gas reaching unsafe levels
- **Advanced inverter technology** provides reliable power to computers and other sensitive equipment
- **i-Monitor LCD** for performance monitoring and diagnostics
- **Parallel with another EU7000is for additional power**
- Integrated **folding handles** with **wheel kit**
- **Oil Alert®**, **Overload Alarm** and **Eco Throttle®**
- **Honda 3-Year Residential Warranty/ Honda 3-Year Commercial Warranty†**



SPECIFICATIONS

EU7000is

Engine	Honda GX390
Displacement	389cc
Max AC Output	7000w max. 120/240V (58.3/29.1A)
Rated AC Output	5500w rated (45.8/22.9A)
Receptacles	20A 125V GFCI Duplex (2) 30A 125V Locking Plug 30A 125/250V Locking Plug
Frequency Regulation	Inverter
Starting System	Electric, Recoil
Fuel Tank Capacity	5.1 gal
Run Time Per Tankful	6.4 hours at rated load 16 hours at 1/4 load
Noise Level**	58 dB(A) at rated load 52 dB(A) at 1/4 load
Dimensions (L x W x H)	33.4" x 27.6" x 28.4"††
Dry Weight	263.2 lbs.
USDA Spark Arrestor	Standard
CO-MINDER™	Standard



Find out more at gen.honda.com.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by American Honda Motor Co., Inc. is under license. Other trademarks and trade names are those of their respective owners. *This product complies with the ANSI/PGMA G300-2018 standard. †Warranty applies to all Honda GX Series Engines and GX Series-powered Honda Power Equipment, 100cc or larger, purchased or put into rental service since January 1, 2010. Exceptions apply. See full warranty details at honda.com. Does not apply to EU1000 models. **Tested in accordance with ISO 9614-2, sound pressure level calculated at 23 Feet (7 meters) using the front plane of the generator (control panel side) per ASHRAE Handbook 2017. ††With handles folded. Please read the owner's manual before operating your Honda Power Equipment and never use in a closed or partly enclosed area where you could be exposed to odorless, poisonous carbon monoxide. Connection of a generator to house power requires a transfer device to avoid possible injury to power company personnel. Consult a qualified electrician. © 2020 American Honda Motor Co., Inc. C1036

